

Martin Aura LED Wash



The MAC Aura is an award-winning wash light that lighting designers have turned to the world over due to its versatility as a powerful beam and wash luminaire of the highest caliber. The result of out-of-the-box creative thinking, it is the first LED moving head wash light to combine multi-colour beam LEDs with a backlight LED array that takes the synthetic look out of LED wash lights.

- Single-lens wash with fully premixed colour
- Broad colour palette, RGBW colour mixing
- Eye-candy Aura effects

Physical

Size of Unit 302 x 302 x 360mm Item Weight 5.6kg Quantity in Case 6

Electrical

Rated Power 260w

Input Power 100-240v AC 50/60Hz Power Connection PowerCON Connector

Mounting Options

Hanging Type Trigger clamp

Freestanding Yes – removing trigger clamp

Expo LX Yes

Optical

Light Source 19 x 10w RGBW LED array system

Beam Angle 11-58°

Colour Temperature 2500 - 10000k

Light Output 2m 1290 Light Output 4m 366 Light Output 6m 180



Control

Control Method DMX

DMX Mode 14ch / 25ch

DMX Channel List See attached links

DMX Connection Types 5pin DMX

Environmental

IP Rating IP20

Cooling Forced air (Regulated fans)

Max Operating Temperature 5-40°

Accessories Included

1 x clamp

1 x Safety chain

1 x Power lead

GOBO

Not available on this unit

Colour

RGBW / CMY colour mixing

Information Links

Manufacturer Link Martin Aura

Data Sheet **Photometry Report**

Data Sheet User Guide

Data Sheet Spec Sheet

Report of Photometry & Chromaticity for Light Source



Product Description


Product Name Martin Aura LED Wash

Sample Number

2020/5/6 15:34:43

Manufacturer Martin Tester HTH

Reviewer





Date(YYYY/MM/DD)

20 Temperature(°C) Re. Humidity(%)

CIE_x	0.2378	Duv	0.0000	
CIE_y	0.1569	λd(nm)	445.6	
CIE_u'	0.2159	Purity(%)	55	
CIE_v'	0.3204	FWHM(nm)	26	
CCT(K)	0	SP ratio	4.25	
Illuminance(lx)	1290	PPFD(µmol/m²s)	38.4	
λp(nm)	448	CRI(Ra)	0	
TLCI(Qa)	0.0	GAI	0.0	
GAI BB8	0	GAI BB15	0	
TM-30 Rf	0	TM-30 Ra	0	

CQS-Qa		U	0 Re(thru R1~R15)		
R1	0.0	R6	0.0	R11	0.0
R2	0.0	R7	0.0	R12	0.0
R3	0.0	R8	0.0	R13	0.0
R4	0.0	R9	0.0	R14	0.0
R5	0.0	R10	0.0	R15	0.0

Flicker Frequency(Hz)

Flicker Index

Flicker %

