



Jands E101 EZICOM Communications Beltpack

Up to 20 remote E101 beltpacks can be connected to the E401 master station.

Physical

Size of Unit	200W x 110H x 55Dmm
Item Weight	0.33kg
Size of unit cased	TBC
Cased weight	N/A
Quantity in Case	5



Electrical

Input Power	24-32VDC beltpack power. Line Signal Level 1mA/V
Power Connection	via 3 pin XLR coms line from E401 Master Station
Current Draw	100mA max

Mounting Options

Rack Mountable	N/A
----------------	-----

Input / Outputs

Coms Line Input	3 pin female XLR
Coms Line Loop Out	3 pin male XLR
Headset in/out	4 pin XLR connector

Parameters

Microphone Type	N/A
Headphone Impedance	N/A
Number of E101's that can be connected to an E401	Up to 20
Program Input sensitivity	– Mic : -55 to -35 dBu
Program Input sensitivity	– Line: -15 to +5 dBu

Compatibility

Coms System	Jands Clearcom RS Series
-------------	--------------------------

Information Links

Manufacturer Link	Jands E101 EZICOM Beltpack Product Page
Datasheet	Jands E101 EZICOM Beltpack User Manual